



Innovation. Passion. Commitment.

SEC 05P



FEATURES

CONTROL PANEL

- Up to 5 control panels can be linked in to one common solution
- Micro-controller based
- 5 zones
- 3 zones programmable as delay, immediate, panic or fire.
- 1 dedicated panic zone
- 1 dedicated fire zone
- Onboard backlit key pad
- 12 LED display
- Two user codes —master and staff
- 3-7 digit user codes
- On board backlit key pad
- Can connect external GSM or landline based voice or voice plus SMS auto dialer
- Individual zone status is indicated on LED display
- Silent arming to silence exit delay audio indication
- Night mode arming to convert delay zones into immediate zones
- Panic, Fire and Quick Arm keys on control panel and remote key pad/s
- Entry / exit delay time programmable from 2 to 255 seconds
- Programmable sounder time from 2 to 20 minutes
- Walk test for sounder free system testing
- Distinct interrupted siren for fire alarm
- Intrusion log
- Can omit one or more zones
- System goes into alarm state after three incorrect code attempts
- Optional chime alert in delay zones
- Non-volatile memory restores multiple programmable settings in case of system reset
- Automatic re-arming in case of alarm at which point open zones will be bypassed
- 7 LEDs indicate operational status
- 5 LEDs indicate individual zone status
- Blown Fuse LED indicator
- Self test on power up / power reset
- Can connect individual piezo sounders and flasher
- Can connect additional common sounder for up to 5 control panels
- Common back end control unit for up to 5 control panels with common sounder and power supply
- Common control unit power supply has provision for built in 12V 7AH SMF battery
- Individual control panel in small sleek ABS housing with keypad cover
- Please refer to product datasheet for full features